INDUSTRIAL COMPONENT DATA

IOA FEED-THRU-DO/NI/EX 1172189 PHOENIX CONTACT Non-incendiary repellent protection device, Ex-ic for Marshal..

Brand: PHOENIX CONTACT | Manufacturer Part Number: IOA FEED-THRU-DO/NI/EX

PRODUCT IMAGE\nNOT AVAILABLE

Manufacturer	PHOENIX CONTACT
MPN / Reference	IOA FEED-THRU-DO/NI/EX
Catalog number	1172189
Category	Interface module
Minimum order	1 Pcs
Document ID	EO-1CB47D7779
Generated	2026-11-18

Product Overview

Non-incendiary repellent protection device, Ex-ic for Marshalling I/O VIP base elements. To limit current (60 mA or 80 mA) and voltage (26.4 V DC) on digital outputs. For example, to activate solenoid valves in the Ex zone (zone 2, CID2).

STRUCTURED PRODUCT DATA

Technical Specifications

No structured technical attributes are currently available. Submit an RFQ for technical review.

Classification & Catalog Path

Catalog path	PHOENIX CONTACT > INTERFACE Components (IF)

REQUEST PRICE, AVAILABILITY & TECHNICAL REVIEW

Send PHOENIX CONTACT / IOA FEED-THRU-DO/NI/EX with the required quantity to info@electricaonline.com or use electricaonline.com/request-quote.

GLOBAL OFFICES

Germany: Lise-Meitner-Straße 13, 89081 Ulm | USA: 16225 Park Ten Pl #500, Houston, TX 77084 | UAE: HDS Business Centre Tower, Cluster M, 33rd Floor, JLT, Dubai

Catalog-generated document. Product names, marks and specifications belong to their respective owners. Verify safety-critical, compatibility and certification requirements against the manufacturer documentation before purchase or installation.