INDUSTRIAL COMPONENT DATA

MINI MCR-EX-IDS-I-I-PT 2908806 PHOENIX CONTACT Ex i-Output Signal Conditioner for Separating and Transferrin..

Brand: PHOENIX CONTACT | Manufacturer Part Number: MINI MCR-EX-IDS-I-I-PT

PRODUCT IMAGE\nNOT AVAILABLE

Manufacturer	PHOENIX CONTACT
MPN / Reference	MINI MCR-EX-IDS-I-I-PT
Catalog number	2908806
Category	Isolation amplifier
Minimum order	1 Pcs
Document ID	EO-A1AF6E1033
Generated	2026-11-19

Product Overview

Ex i-Output Signal Conditioner for Separating and Transferring 0mA/4mA Signals... 20 mA from the control system to an intrinsically safe load in the Ex zone. With HART transparency, no-load voltage: 27 V DC, Standard configuration, Safety Integrity Level (SIL, IEC 61508): 3, Push-in connection

STRUCTURED PRODUCT DATA

Technical Specifications

No structured technical attributes are currently available. Submit an RFQ for technical review.

Classification & Catalog Path

Catalog path	PHOENIX CONTACT > INTERFACE Components (IF)

REQUEST PRICE, AVAILABILITY & TECHNICAL REVIEW

Send PHOENIX CONTACT / MINI MCR-EX-IDS-I-I-PT with the required quantity to info@electricaonline.com or use electricaonline.com/request-quote.

GLOBAL OFFICES

Germany: Lise-Meitner-Straße 13, 89081 Ulm | USA: 16225 Park Ten Pl #500, Houston, TX 77084 | UAE: HDS Business Centre Tower, Cluster M, 33rd Floor, JLT, Dubai

Catalog-generated document. Product names, marks and specifications belong to their respective owners. Verify safety-critical, compatibility and certification requirements against the manufacturer documentation before purchase or installation.