

INDUSTRIAL COMPONENT DATA

FLKM-PA-D37/ETHA 1076338 PHOENIX CONTACT VARIOFACE front adapter for Siemens SIMATIC

Brand: PHOENIX CONTACT | Manufacturer Part Number: FLKM-PA-D37/ETHA



Manufacturer	PHOENIX CONTACT
MPN / Reference	FLKM-PA-D37/ETHA
Catalog number	1076338
Category	Accessories/spare parts for controls
Minimum order	1 Pcs
Document ID	EO-478205DAC5
Generated	2026-08-02

Product Overview

VARIOFACE front adapter for Siemens SIMATIC

VARIOFACE front adapter for Siemens SIMATIC® ET 200SP HA with a 37-pin D-SUB blade for 24 V DC and analog digital peripheral modules, max. 32 channel connection

VARIOFACE front adapter for Siemens SIMATIC® ET 200SP HA, with a 37-pos. D-SUB male strip for digital 24 V DC and analog peripheral modules, max. 32 channels can be connected

STRUCTURED PRODUCT DATA

Technical Specifications

No structured technical attributes are currently available. Submit an RFQ for technical review.

Classification & Catalog Path

Catalog path PHOENIX CONTACT > INTERFACE Components (IF)

Additional Product Information

Technical dataProduct propertiesProduct type Front adapter

Product family VARIOFACE

Data management status

Article revision 02

Insulation characteristics: Air clearances and creepage distances

Insulation Functional insulation

Overvoltage category II

Pollution degree 2

Electrical propertiesOperating voltage (AC) <= 30 V AC

Operating voltage (DC) <= 60 V DC

Nominal operating mode 100% operating factor

Current (per branch) ≤ 1 A
Current (Voltage supply via D-SUB) ≤ 2 A
Current (Voltage supply via screw connection) ≤ 10 A
Air clearances and creepage distances
Rated insulation voltage 63 V
Rated surge voltage 0.6 kV (1.2/50 us)
Supported controller SIEMENS ET 200SP HA
Suitable terminal block 6DL1193-6TP00-0BH1
6DL1193-6TP00-0DH1
6DL1193-6TP00-0BM1
6DL1193-6TP00-0DM1
Suitable I/O module 6DL1131-6BH00-0PH1 (Terminal Block H1/M1)
6DL1131-6BL00-0PH1 (Terminal Block H1/M1)
6DL1131-6TH00-0PH1 (Terminal Block H1/M1)
6DL1132-6BH00-0PH1 (Terminal Block H1/M1)
6DL1132-6BL00-0PH1 (Terminal Block H1/M1)
6DL1133-6EW00-0PH1 (Terminal Block H1/M1)
6DL1134-6JH00-0PH1 (Terminal Block H1/M1)
6DL1134-6TH00-0PH1 (Terminal Block H1/M1)
6DL1135-6TF00-0PH1 (Terminal Block H1/M1)
Connection dataConnection 1 (control level)
Connection method Plug-in connection
Number of positions 36
Connection 2 (field level)
Connection in acc. with standard IEC 60807-2
Connection method D-SUB pin strip
Screw thread UNC 4-40
Number of connections 1
Number of positions 37
Insertion/withdrawal cycles > 500
Pitch 2.77 mm
Conn...

REQUEST PRICE, AVAILABILITY & TECHNICAL REVIEW

Send PHOENIX CONTACT / FLKM-PA-D37/ETHA with the required quantity to info@electricaonline.com or use electricaonline.com/request-quote.

GLOBAL OFFICES

Germany: Lise-Meitner-Straße 13, 89081 Ulm | USA: 16225 Park Ten Pl #500, Houston, TX 77084 | UAE: HDS Business Centre Tower, Cluster M, 33rd Floor, JLT, Dubai

Catalog-generated document. Product names, marks and specifications belong to their respective owners. Verify safety-critical, compatibility and certification requirements against the manufacturer documentation before purchase or installation.