

INDUSTRIAL COMPONENT DATA

MKDS 1/ 2-3,5-HT BK R24 KP 1715267 PHOENIX CONTACT

Terminal for printed circuit board, rated voltage: 200 V,..

Brand: PHOENIX CONTACT | Manufacturer Part Number: MKDS 1/ 2-3,5-HT BK R24 KP



Manufacturer	PHOENIX CONTACT
MPN / Reference	MKDS 1/ 2-3,5-HT BK R24 KP
Catalog number	1715267
Category	Printed circuit board terminal
Minimum order	280 Pcs
Document ID	EO-2786ECE6EC
Generated	2026-08-04

Product Overview

Terminal for printed circuit board, rated voltage: 200 V, pitch: 3.5 mm, number of poles: 2, type of connection: Connection by screw with capsule-traction, assembly: Soldering THR, color: black

Terminal block for printed circuit board, nominal current: 13.5 A, nominal voltage (III/2): 200 V, nominal section: 1.5 mm², number of potentials: 2, number of rows: 1, number of poles per row: 2, family of articles: MKDS 1/.. -HT, pitch: 3.5 mm, connection type: Screw connection with traction capsule, screw clamping shape: L Longitudinal slot, mounting: Weld THR, conductor connection direction/printed circuit board: 0 °, color: black, Pin arrangement: Linear pin arrangement, Pin length [P]: 1.65 mm, number of solder pins per potential: 1, Packing Type: 24mm Wide Strap

STRUCTURED PRODUCT DATA

Technical Specifications

No structured technical attributes are currently available. Submit an RFQ for technical review.

Classification & Catalog Path

Catalog path **PHOENIX CONTACT > PCB Connectors (PCC)**

REQUEST PRICE, AVAILABILITY & TECHNICAL REVIEW

Send PHOENIX CONTACT / MKDS 1/ 2-3,5-HT BK R24 KP with the required quantity to info@electricaonline.com or use electricaonline.com/request-quote.

GLOBAL OFFICES

Germany: Lise-Meitner-Straße 13, 89081 Ulm | USA: 16225 Park Ten Pl #500, Houston, TX 77084 | UAE: HDS Business Centre Tower, Cluster M, 33rd Floor, JLT, Dubai

Catalog-generated document. Product names, marks and specifications belong to their respective owners. Verify safety-critical, compatibility and certification requirements against the manufacturer documentation before purchase or installation.