

INDUSTRIAL COMPONENT DATA

590.FEM16005 SCAME SWITCH DISCONNECTOR 160A 3P+N IP65

Brand: SCAME | Manufacturer Part Number: 590.FEM16005



Manufacturer	SCAME
MPN / Reference	590.FEM16005
Catalog number	16005
Category	Switch disconnecter
Minimum order	1 Pcs
Document ID	EO-17A52182EE
Generated	2026-08-02

Product Overview

SWITCH DISCONNECTOR 160A 3P+N IP65

MANOEUVRING INT. 160A 3P+N IP65

160A 3P+N IP65 315x410x150mm FR3 IK08 EMERGENCY YELLOW/RED FIRE RATED

STRUCTURED PRODUCT DATA

Technical Specifications

No structured technical attributes are currently available. Submit an RFQ for technical review.

Classification & Catalog Path

Catalog path SCAME > Switches - SCAME

Additional Product Information

Commercial SeriesISOLATORS-FR SeriesSynthetical descriptionSWITCH DISCONNECTORConstruction typeEnclosedMounting versionSURFACE MOUNTINGMaterialDIE-CAST ALUMINIUMProtection degree IP65Installation temperature-25°C/+60°CTypeEMERGENCYColourYELLOW/REDRated current160APoles3P+NSwitch sizeFR3Rated voltage690VDimensions315x410x150mmNotesFIRE RATEDFire rated classF400 (120min)Protection degree IKIK08Rated insulation voltage (Ui)800VACRated impulse voltage (Uimp)8kVThermal current (Ithe)160ACurrent (Ie) in AC21A (415V)160ACurrent (Ie) in AC22A (415V)160ACurrent (Ie) in AC23A (415V)160APower AC23A (415V)69kWShort-time current3kA Icw(1s)Conditional short circuit cur.69kAeffAssociate fuse - type gG125ATerminals - Flexible wires10-70mm²Terminals - Rigid wires10-70mm²Catalogue notesHandle padlockable in OFF (3 padlocks) and ON (1 padlock) positionEquipped with door interlockBlank sidesWith late break and early make neutral pole

REQUEST PRICE, AVAILABILITY & TECHNICAL REVIEW

Send SCAME / 590.FEM16005 with the required quantity to info@electricaonline.com or use electricaonline.com/request-quote.

GLOBAL OFFICES

Germany: Lise-Meitner-Straße 13, 89081 Ulm | USA: 16225 Park Ten Pl #500, Houston, TX 77084 | UAE: HDS Business Centre Tower, Cluster M, 33rd Floor, JLT, Dubai

Catalog-generated document. Product names, marks and specifications belong to their respective owners. Verify safety-critical, compatibility and certification requirements against the manufacturer documentation before purchase or installation.