

INDUSTRIAL COMPONENT DATA

590.FGE31505 SCAME SWITCH DISCONNECTOR 315A 3P+N IP65

Brand: SCAME | Manufacturer Part Number: 590.FGE31505



Manufacturer	SCAME
MPN / Reference	590.FGE31505
Catalog number	31505
Category	Switch disconnector
Minimum order	1 Pcs
Document ID	EO-0A65D2852A
Generated	2026-08-02

Product Overview

SWITCH DISCONNECTOR 315A 3P+N IP65

MANOEUVRING INT. 315A 3P+N IP65

315A 3P+N IP65 500x700x250mm FR5 IK10 GENERAL GREY/BLACK FIRE RATED

STRUCTURED PRODUCT DATA

Technical Specifications

No structured technical attributes are currently available. Submit an RFQ for technical review.

Classification & Catalog Path

Catalog path SCAME > Switches - SCAME

Additional Product Information

Commercial SeriesISOLATORS-FR SeriesSynthetical descriptionSWITCH DISCONNECTORConstruction typeEnclosedMounting versionSURFACE MOUNTINGMaterialMETALProtection degree IPIP65Installation temperature-25°C/+60°CTypeGENERALColourGREY/BLACKRated current315APoles3P+NSwitch sizeFR5Rated voltage690VDimensions500x700x250mmNotesFIRE RATEDFire rated classF400 (120min)Protection degree IKIK10Rated insulation voltage (Ui)1000VACRated impulse voltage (Uimp)8kVThermal current (Ithe)400ACurrent (Ie) in AC21A (415V)400ACurrent (Ie) in AC22A (415V)315ACurrent (Ie) in AC23A (415V)315APower AC23A (415V)165kWShort-time current13kA Icw(1s)Conditional short circuit cur.50kAeffAssociate fuse - type gG315ATerminals - Rigid wires10-70mm²Terminal bolt sizeM10Palm width25mmCatalogue notesEquipped with door interlockGland plate cable entry on bottom sideHandle padlockable in OFF (3 padlocks) and ON (1 padlock) positionWith late break and early make neutral pole

REQUEST PRICE, AVAILABILITY & TECHNICAL REVIEW

Send SCAME / 590.FGE31505 with the required quantity to info@electricaonline.com or use electricaonline.com/request-quote.

GLOBAL OFFICES

Germany: Lise-Meitner-Straße 13, 89081 Ulm | USA: 16225 Park Ten Pl #500, Houston, TX 77084 | UAE: HDS Business Centre Tower, Cluster M, 33rd Floor, JLT, Dubai

Catalog-generated document. Product names, marks and specifications belong to their respective owners. Verify safety-critical, compatibility and certification requirements against the manufacturer documentation before purchase or installation.