

INDUSTRIAL COMPONENT DATA

590.YA806B SCAME SWITCH DISCONNECTOR 80A 6P B

Brand: SCAME | Manufacturer Part Number: 590.YA806B



Manufacturer	SCAME
MPN / Reference	590.YA806B
Catalog number	10000
Category	Switch disconnecter
Minimum order	1 Pcs
Document ID	EO-2C7AED8AA3
Generated	2026-08-02

Product Overview

SWITCH DISCONNECTOR 80A 6P B
BODY INT. MANEUVER 80A 6P B
80A 6P Y4 BOX (B)

STRUCTURED PRODUCT DATA

Technical Specifications

No structured technical attributes are currently available. Submit an RFQ for technical review.

Classification & Catalog Path

Catalog path SCAME > Switches - SCAME

Additional Product Information

Commercial SeriesCOMMAND SeriesSynthetical descriptionSWITCH DISCONNECTORConstruction typeOpen typeMounting versionBMaterialTHERMOPLASTICInstallation temperature-25°C/+60°CTypeBOX (B)Rated current80APoles6PSwitch sizeY4Rated voltage690VRated insulation voltage (Ui)690VACRated impulse voltage (Uimp)8kVThermal current (Ithe)100ACurrent (Ie) in AC21A (415V)100ACurrent (Ie) in AC21A (500V)100ACurrent (Ie) in AC21A (690V)100ACurrent (Ie) in AC22A (415V)80ACurrent (Ie) in AC22A (500V)80ACurrent (Ie) in AC22A (690V)80ACurrent (Ie) in AC23A (415V)80ACurrent (Ie) in AC23A (500V)63ACurrent (Ie) in AC23A (690V)63APower AC23A (415V)37kWShort-time current1,5kA Icw(1s)Conditional short circuit cur.50kAeffAssociate fuse - type gG80ATerminals - Flexible wires10-50mm²Terminals - Rigid wires10-50mm²Catalogue notesEquipped with direct handleBOX (B) = Base mountingDIN rail / screw fixing

REQUEST PRICE, AVAILABILITY & TECHNICAL REVIEW

Send SCAME / 590.YA806B with the required quantity to info@electricaonline.com or use electricaonline.com/request-quote.

GLOBAL OFFICES

Germany: Lise-Meitner-Straße 13, 89081 Ulm | USA: 16225 Park Ten Pl #500, Houston, TX 77084 | UAE: HDS Business Centre Tower, Cluster M, 33rd Floor, JLT, Dubai

Catalog-generated document. Product names, marks and specifications belong to their respective owners. Verify safety-critical, compatibility and certification requirements against the manufacturer documentation before purchase or installation.