

INDUSTRIAL COMPONENT DATA

590.YA322B SCAME SWITCHING UNIT BASE MOUNT.32A 2P

Brand: SCAME | Manufacturer Part Number: 590.YA322B



Manufacturer	SCAME
MPN / Reference	590.YA322B
Catalog number	10000
Category	Switch disconnecter
Minimum order	6 Pcs
Document ID	EO-38A789A805
Generated	2026-07-31

Product Overview

SWITCHING UNIT BASE MOUNT.32A 2P
INT. BODY MANEUVER 32A 2P B
32A 2P Y1 BOX (B)

STRUCTURED PRODUCT DATA

Technical Specifications

No structured technical attributes are currently available. Submit an RFQ for technical review.

Classification & Catalog Path

Catalog path	SCAME > Switches - SCAME
--------------	--------------------------

Additional Product Information

Commercial SeriesCOMMAND SeriesSynthetical descriptionSWITCH DISCONNECTORConstruction typeOpen typeMounting versionBMaterialTHERMOPLASTICInstallation temperature-25°C/+60°CTypeBOX (B)Rated current32APoles2PSwitch sizeY1Rated voltage690VRated insulation voltage (Ui)690VACRated impulse voltage (Uimp)4kVThermal current (Ithe)40ACurrent (Ie) in AC21A (415V)40ACurrent (Ie) in AC21A (500V)32ACurrent (Ie) in AC21A (690V)32ACurrent (Ie) in AC22A (415V)32ACurrent (Ie) in AC22A (500V)32ACurrent (Ie) in AC22A (690V)32ACurrent (Ie) in AC23A (415V)32ACurrent (Ie) in AC23A (500V)25ACurrent (Ie) in AC23A (690V)25ACurrent (Ie) in AC3 (415V)25ACurrent (Ie) in AC3 (690V)18ACurrent (Ie) in DC22A (250V)32ACurrent (Ie) in DC22A (600V)10APower AC23A (415V)15kWShort-time current400A Icw(1s)Conditional short circuit cur.10kAeffAssociate fuse - type gG32ATerminals - Flexible wires1.5-10mm²Terminals - Rigid wires1.5-16mm²Catalogue notesBOX (B) = Base mountingDIN rail fixing

REQUEST PRICE, AVAILABILITY & TECHNICAL REVIEW

Send SCAME / 590.YA322B with the required quantity to info@electricaonline.com or use electricaonline.com/request-quote.

GLOBAL OFFICES

Germany: Lise-Meitner-Straße 13, 89081 Ulm | USA: 16225 Park Ten Pl #500, Houston, TX 77084 | UAE: HDS Business Centre Tower, Cluster M, 33rd Floor, JLT, Dubai

Catalog-generated document. Product names, marks and specifications belong to their respective owners. Verify safety-critical, compatibility and certification requirements against the manufacturer documentation before purchase or installation.