

INDUSTRIAL COMPONENT DATA

590.YA802B SCAME SWITCHING UNIT BASE MOUNT.80A 2P

Brand: SCAME | Manufacturer Part Number: 590.YA802B



Manufacturer	SCAME
MPN / Reference	590.YA802B
Catalog number	10000
Category	Switch disconnecter
Minimum order	6 Pcs
Document ID	EO-3D7040B5AC
Generated	2026-08-01

Product Overview

SWITCHING UNIT BASE MOUNT.80A 2P
INT. BODY MANEUVER 80A 2P B
80A 2P Y2 BOX (B)

STRUCTURED PRODUCT DATA

Technical Specifications

No structured technical attributes are currently available. Submit an RFQ for technical review.

Classification & Catalog Path

Catalog path	SCAME > Switches - SCAME
--------------	--------------------------

Additional Product Information

Commercial SeriesCOMMAND SeriesSynthetical descriptionSWITCH DISCONNECTORConstruction typeOpen typeMounting versionBMaterialTHERMOPLASTICInstallation temperature-25°C/+60°CTypeBOX (B)Rated current80APoles2PSwitch sizeY2Rated voltage690VRated insulation voltage (Ui)690VACRated impulse voltage (Uimp)4kVThermal current (Ithe)80ACurrent (Ie) in AC21A (415V)80ACurrent (Ie) in AC21A (500V)80ACurrent (Ie) in AC21A (690V)80ACurrent (Ie) in AC22A (415V)80ACurrent (Ie) in AC22A (500V)80ACurrent (Ie) in AC22A (690V)80ACurrent (Ie) in AC23A (415V)67ACurrent (Ie) in AC23A (500V)67ACurrent (Ie) in AC23A (690V)38ACurrent (Ie) in AC3 (415V)55ACurrent (Ie) in AC3 (690V)32ACurrent (Ie) in DC22A (250V)63APower AC23A (415V)37kWShort-time current1,5kA Icw(1s)Conditional short circuit cur.10kAeffAssociate fuse - type gG80ATerminals - Flexible wiresTerminals - Rigid wires10-35mm²Catalogue notesBOX (B) = Base mountingDIN rail fixing

REQUEST PRICE, AVAILABILITY & TECHNICAL REVIEW

Send SCAME / 590.YA802B with the required quantity to info@electricaonline.com or use electricaonline.com/request-quote.

GLOBAL OFFICES

Germany: Lise-Meitner-Straße 13, 89081 Ulm | USA: 16225 Park Ten Pl #500, Houston, TX 77084 | UAE: HDS Business Centre Tower, Cluster M, 33rd Floor, JLT, Dubai

Catalog-generated document. Product names, marks and specifications belong to their respective owners. Verify safety-critical, compatibility and certification requirements against the manufacturer documentation before purchase or installation.