

INDUSTRIAL COMPONENT DATA

5ST1325 SIEMENS Set of infeed terminals for main conductor circuit breaker (SHU), for 50 mm2 1 set 3 infeed ..

Brand: SIEMENS | Manufacturer Part Number: 5ST1325



Manufacturer	SIEMENS
MPN / Reference	5ST1325
Catalog number	10000
Category	Accessories/spare parts for low-voltage switch technology
Minimum order	1 Pcs
Document ID	EO-BC89059BB1
Generated	2026-08-04

Product Overview

Set of infeed terminals for main conductor circuit breaker (SHU), for 50 mm2 1 set=3 infeed terminals and 1 N terminal and 1 PE terminal

STRUCTURED PRODUCT DATA

Technical Specifications

No structured technical attributes are currently available. Submit an RFQ for technical review.

Classification & Catalog Path

Catalog path	SIEMENS > POWER DISTRIBUTION AND LOW VOLTAGE SWITCHGEAR > Other Modular Systems
--------------	---

Additional Product Information

ETIM: EC002498 - Accessories/spare parts for low-voltage switch technology

Value Unit

Type of accessory/spare part (EF000215) Other

Set of infeed terminals for main conductor circuit breaker (SHU), for 50 mm2 1 set=3 infeed terminals and 1 N terminal and 1 PE terminal

Model

product brand name SENTRON

Accessories

Accessories others

Certificates

General Product Approval Declaration of Conformity

Miscellaneous

Further information

Information- and Downloadcenter (Catalogs, Brochures, etc.) <http://www.siemens.com/lowvoltage/catalogs>

Industry Mall (Online ordering system)<https://mall.industry.siemens.com/mall/en/en/Catalog/product?mlfb=5ST1325>

Service&Support (Manuals, Certificates, Characteristics,

FAQs,...)<https://support.industry.siemens.com/cs/ww/en/ps/5ST1325>

Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams,
...) http://www.automation.siemens.com/bilddb/cax_en.aspx?mlfb=5ST1325

CAX-Online-Generator <http://www.siemens.com/cax>

Tender specifications <http://www.siemens.com/specifications>

Product

Article Number (Market Facing Number) 5ST1325

Product Description Set of infeed terminals for main conductor circuit breaker (SHU), for 50 mm² 1 set=3 infeed terminals and 1 N terminal and 1 PE terminal

Product family Ordering Data Overview

Product Lifecycle (PLM) PM400:Phase Out Started

PLM Effective Date Product phase-out since: 30.04.2020

Notes Successor:Further information about local contact: www.siemens.com/lowvoltage/contact

Price data

Price Group....

REQUEST PRICE, AVAILABILITY & TECHNICAL REVIEW

Send SIEMENS / 5ST1325 with the required quantity to info@electricaonline.com or use electricaonline.com/request-quote.

GLOBAL OFFICES

Germany: Lise-Meitner-Straße 13, 89081 Ulm | USA: 16225 Park Ten Pl #500, Houston, TX 77084 | UAE: HDS Business Centre Tower, Cluster M, 33rd Floor, JLT, Dubai

Catalog-generated document. Product names, marks and specifications belong to their respective owners. Verify safety-critical, compatibility and certification requirements against the manufacturer documentation before purchase or installation.